

FG-A

Alarm Unit for Water and Acids Leak Detection

Product Datasheet





- ► Analog Leak Detection System
- Simple Detection Without Location
- ▶ Three LED Indicators
- ▶ Two Output Relays
- Adjustable Sensitivity

Description

The FG-A alarm unit is designed to be used with TTK analog sense cables and probes to give immediate detection of liquid leaks (water, acids or base).

System Responses:

- Leak Detection: Triggers an audible alarm, activates the red LED, and activates the leak relay.
- Cable Break: Triggers an audible alarm, activates the yellow LED, and activates the cable break relay.

Alarm Control:

■ The "SOUND OFF" button on the front panel allows manual muting of the audible alarm. However, the LED and relay remain activated until the fault is resolved. Once corrected, the system automatically returns to normal status.

Key Advantages

- Zone Control: The FG-A unit can control up to 49 ft (15 m) of sense cable.
- Adjustable Sensitivity: The sensitivity of the unit is adjustable via the potentiometer located on the PCB.
- Fault Detection: The system detects cable break faults to ensure reliable monitoring.
- Clear Alerts: Visual and audible indicators differentiate between leak and cable break faults.
- Easy Installation: Easily accessible terminals enable quick and hassle-free installation.
- Reliable & Simple: The FG-A unit is accurate and user-friendly, making it ideal for small applications where precise leak location is not required.

Panel Description

- 1: The leak signal (red LED) indicates that the system has detected a liquid leak.
- 2: The continuity signal (yellow LED) indicates that the system has detected a circuit interruption.
- 3: The power supply signal (green LED) indicates that the system is in normal operation.
- 4: The button is used to stop the audible alarm.



Identification Codes

| FG-A F | Leak Detection Alarm Unit (Wall Mounted) 240VAC - Water & Acids Detection |
|--------------|---|
| Accessories: | |
| FG-CLC | Leader Cable 11.5 ft (3.5 m) |
| FG-TMX | End Termination |
| CF-EC100 | 100 Hold-down Clips with Adhesive |
| ES-EC | 40 Signal Tags |

Certifications



All the connections in the FG-A alarm unit must be done with the power supply switched off. Read carefully the installation procedure for the FG-A alarm unit.

This brochure has been carefully prepared to ensure technical accuracy but is only intended for promotional use. TTK cannot guarantee that the information contained herein contains no errors or omissions, and hence does not accept responsibility related to the use of its equipment. TTK maintain its obligations set forth in the Standard Terms and Conditions of Sale and will not, under any circumstances, assume liability for any incidental damages, indirect or consequential, arising from the sale, resale, use or misuse of this product. The purchaser(s) accept their responsibility as the sole judge(s) of the adaptability of the product for the intended use.

FG-NET, FG-SYS and TOPSurveillance are trademarks of TTK S.A.S. © TTK 2025

- TTK USA Inc. / 100 S. Broad Street, Suite 730 Philadelphia, PA 19110 / Tel. +1 610 304 2270 / www.ttkusa.com / sales@ttkusa.com
- TTK Headquarters / 19, rue du Général Foy / 75008 Paris / France / T:+33.1.56.76.90.10 / F:+33.1.55.90.62.15 / www.ttk.fr / ventes@ttk.fr